

## SÈRIE 2

### Primera part


#### Exercici 1

Q1 a      Q2 a      Q3 d      Q4 b      Q5 c

#### Exercici 2

	$p$	$b$	$e$	$a$
	0	0	0	1
	0	0	1	1
	0	1	0	0
a)	0	1	1	1
	1	0	0	0
	1	0	1	1
	1	1	0	0
	1	1	1	1

b)  $a = e + \bar{p} \cdot \bar{b}$



### Segona part

#### OPCIÓ A

#### Exercici 3

a)  $R_{\text{eq}} = \left( \frac{1}{R_1} + \frac{1}{R_2} \right)^{-1} = 18 \, \Omega$


b)  $I = \frac{U}{R_{\text{eq}}} = 12,7 \, \text{A}$

c)  $P = \frac{U^2}{R_{\text{eq}}} = 2,938 \, \text{kW}$

d)  $c = E p = P t p = 0,5114 \, \text{€}$

**Exercici 4**

a)  $P = \Gamma \omega = c l \omega = \frac{cU}{R} \omega - \frac{c^2}{R} \omega^2 = (0,54 \omega - 900 \cdot 10^{-6} \omega^2) \text{ W}$



c)  $E = P_{\text{elèc}} t = U I t = 1,4 \text{ MJ} = 388,8 \text{ W}\cdot\text{h}$

**OPCIÓ B**

**Exercici 3**

a)  $\varphi_1 = \arcsin \frac{L}{4L} = 14,48^\circ$        $\varphi_2 = \arcsin \frac{L}{3L} = 19,47^\circ$

b)  $\sum \mathbf{F}_{\text{ext}} = 0 \rightarrow \begin{cases} F_1 \cos \varphi_1 - F_2 \cos \varphi_2 = 0 \\ F_1 \sin \varphi_1 + F_2 \sin \varphi_2 - mg = 0 \end{cases}$

$$F_1 = mg \frac{\cos \varphi_2}{\sin(\varphi_1 + \varphi_2)} = 745,1 \text{ N}$$

$$F_2 = mg \frac{\cos \varphi_1}{\sin(\varphi_1 + \varphi_2)} = 765,2 \text{ N}$$

c)  $\sigma_1 = \frac{F_1}{S}$  ;  $\sigma_2 = \frac{F_2}{S} \rightarrow \frac{\sigma_1}{\sigma_2} = \frac{F_1}{F_2} = 0,9737$

**Exercici 4**

a)  $E_{\text{elèc}} = m p \eta_{\text{elèc}} = 64,85 \text{ MW}\cdot\text{h}$

$$P_{\text{elèc}} = \frac{E_{\text{elèc}}}{\Delta t} = 2,702 \text{ MW}$$

b)  $E_{\text{tèrmica}} = m p (1 - \eta_{\text{elèc}}) \eta_{\text{tèrmic}} \rightarrow m_{\text{aigua}} = \frac{E_{\text{tèrmica}}}{c_e \Delta t} = \frac{m p (1 - \eta_{\text{elèc}}) \eta_{\text{tèrmic}}}{c_e \Delta t} = 2,93 \cdot 10^6 \text{ kg}$

c)  $q = \frac{m_{\text{aigua}}}{24 \cdot 3600 \rho_{\text{aigua}}} = 33,91 \text{ l/s}$

**SÈRIE 1**

**Primera part**


**Exercici 1**

Q1 a      Q2 b      Q3 d      Q4 d      Q5 b

**Exercici 2**

<i>c</i>	<i>v</i>	<i>t</i>	<i>d</i>
0	0	0	0
0	0	1	0
0	1	0	1
1	0	1	0
1	0	1	1
1	1	0	1
1	1	1	1

a)      b)  $d = c + v \cdot \bar{t}$



**Segona part**

OPCIÓ A

**Exercici 3**

a)  $\varphi = \arctan \frac{2L}{3L} = 33,69^\circ$

b)  $\sum M(O) = 0 \rightarrow 3LT \sin \varphi - 2Lmg = 0 \rightarrow T = \frac{2}{3} \frac{mg}{\sin \varphi} = 176,8 \text{ N}$

c)  $\sum F_{\text{ext}} = 0 \rightarrow \begin{cases} F_h - T \cos \varphi = 0 \\ F_v + T \sin \varphi - mg = 0 \end{cases} \rightarrow \begin{cases} F_h = \frac{2}{3} \frac{mg}{\sin \varphi} \cos \varphi = mg = 147,1 \text{ N} \\ F_v = mg - T \sin \varphi = 49,04 \text{ N} \end{cases}$

d)  $\sigma = \frac{T}{s} = 14,14 \text{ MPa}$

### Exercici 4

a)  $P = q \rho_{\text{aigua}} c_{\text{aigua}} \Delta t = 24,04 \text{ kW}$

b)  $\eta = \frac{P}{\rho_c q_{\text{comb}}} = 0,7726$

c)  $t = \frac{V}{q} = 10,87 \text{ min} = 652,2 \text{ s}$        $m = t q_{\text{comb}} = 332,6 \text{ g}$

### OPCIÓ B

### Exercici 3


a)  $P = \frac{U^2}{R} \rightarrow R = \frac{U^2}{P} = 26,45 \Omega$

b)  $R = \rho \frac{L}{S} \rightarrow L = \frac{RS}{\rho} = 3,324 \text{ m}$

c)  $E = P t = 2,25 \text{ kW} \cdot \text{h} = 8,1 \text{ MJ}$

### Exercici 4

a)  $\omega = \frac{U - c I}{R} \rightarrow I = \frac{U - c \omega}{R}$



b)  $\Gamma_{\text{màx}} = c I_{\text{màx}} = 0,18 \text{ Nm}$ . Es produeix per a  $\omega = 0$ , és a dir en arrencar.

c)  $E_{\text{elèc}} = P_{\text{elèc}} \Delta t = U I \Delta t = 3,456 \text{ kJ} = 0,96 \text{ W} \cdot \text{h}$